


AXRX-QDM-III

Quick-deploy 2-way diversity COFDM receiver for portable applications.



Key features:

- Updated compact design
- Larger 4-line LED display
- Available in 2 or 5.8 GHz frequency bands
- -95dBm plus receiver sensitivity
- Ethernet GUI setup and control
- 6, 7, or 8 MHz DVB-T bandwidth
- QPSK, 16QAM, 64QAM DVB-T constellations
- 1/2, 2/3, 3/4, 5/6, and 7/8 DVB-T FEC
- 1/4, 1/8, 1/16, and 1/32 DVB-T guard interval
- AVC h.264 / MPEG-4 Part 10 compression
- Optional RTSP/UDP streaming
- 1x HD-SDI, 1x HD-SDI/ASI output (BNC female)
- 2x embedded audio pairs, 1x analog audio pair
- 9 - 16 VDC power input
- 20W power consumption
- Available with Anton Bauer or IDX battery mounts, optional power pass-through
- Standard dimensions: 6.43"H X 3.59"W X 2.10"D
- Weight: 1.9 lbs.

• Supported 3G resolutions:

- 1920X1080p, 60/59.94/50 Hz
(via Level A or Level B dual link)

• Supported HD resolutions:

- 1920X1080i, 60/59.94/50 Hz
- 1920X1080p, 30/29.97/25/24/23.97 Hz
- 1920X1080psf, 30/29.97/25/24/23.97 Hz
- 1280X720p, 60/59.94/50 Hz

• Supported SD resolutions:

- 720X480i, 59.94 - 720X576i, 50 Hz

• Optional UHF input configuration

- (2) 150 - 850 MHz UHF inputs
- Requires external block down converters (BDCs) not included

